



Statement of Volatility – Dell Latitude E6440

⚠ CAUTION: A CAUTION indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

The **Dell Latitude E6440** contains both volatile and non-volatile (NV) components. Volatile components lose their data immediately after power is removed from the component. Non-volatile (NV) components continue to retain their data even after power is removed from the component. The following NV components are present on the **Dell Latitude E6440** system board.

Table 1. List of Non-Volatile Components on System Board

| Description | Reference Designator | Volatility Description | User Accessible for external data | Remedial Action (Action necessary to prevent loss of data) |
|---|--|--|-----------------------------------|--|
| Embedded Flash in embedded controller MEC5075 | U51 | 288 KB of embedded Flash memory for keyboard controller BIOS code, asset tag and BIOS passwords | No | N/A |
| Panel EEDID EEPROM | Part of panel assembly | Non Volatile memory, 512 bytes. | No | Part of panel assembly |
| System BIOS | U53 | Non Volatile memory, 32 Mbit (4 MB), System BIOS and Video BIOS for basic boot operation, PSA (on board diagnostics), PXE diagnostics. | No | N/A |
| Video BIOS | Embedded in system BIOS | Non Volatile memory, 512 kbit (64 KB), Graphics system BIOS. | No | N/A |
| System Memory – DDR3L memory | Two SODIMM connectors: JDIMM1,2 | Volatile memory in OFF state  NOTE: See state definitions later in text. One to two modules must be populated. System memory size will depend on SODIMM modules and must be between 2 GB and 8 GB. | Yes | Power off system |
| System memory SPD EEPROM | On System memory SODIMM(s) – 1-2 present | Non Volatile memory 512 Bytes. Stores memory manufacturer data and timing information for correct operation of system memory. | No | N/A |

| Description | Reference Designator | Volatility Description | User Accessible for external data | Remedial Action (Action necessary to prevent loss of data) |
|---|---|--|-----------------------------------|--|
| RTC CMOS – BBRAM (battery backed up) | UH1 | Non Volatile memory, 64 Bytes. Stores CMOS information. | No | N/A |
| Video memory – frame buffer | For UMA platform: Using system memory For E6540 DSC platform: UV3, UV4, UV5, UV6, UV7, UV8, UV9, UV10, For E6440 DSC platform: UV3, UV4, UV5, UV6, | Volatile memory in off state. 2 GB GDDR5 for discrete graphics systems. | No | N/A |
| Intel ME Firmware | U52 | Non Volatile memory, 32 Mbit (4 MB), Intel ME firmware for system configuration, security and protection | No | N/A |
| Hard drive(s) | User replaceable - one or two. | Non Volatile magnetic media, various sizes in GB. May also be SSD (solid state flash drive). | Yes | Low level format |
| CD-ROM/RW/ DVD/ DVD+RW/ Diskette Drives | User replaceable | Non Volatile optical media. | Yes | Low level format/erase |

△ CAUTION: All other components on the system board lose data if power is removed from the system. Primary power loss (unplugging the power cord and removing the battery) destroys all user data on the memory (DDR3, 1067 MHz). Secondary power loss (removing the on-board coin-cell battery) destroys system data on the system configuration and time-of-day information.